

OSD830T/OSD830R DIGITAL VIDEO, AUDIO AND DATA TRANSCIVER PAIR

APPLICATIONS


- ▲ High quality CCTV networks requiring full duplex data and/or audio transmission between cameras and their control centre
- ▲ Transportation communications systems
- ▲ Broadcast television systems
- ▲ Extremely high quality video conferencing



FEATURES AND BENEFITS

- ▲ One way optic transmission of PAL, NTSC or SECAM video plus full duplex transmission of
 - two audio channels
 - three data channels
- ▲ one relay contact channel
- ▲ Studio quality 10 bit video and 24 bit audio
- ▲ Remote control of Pan, Tilt and Zoom for video surveillance.
- ▲ Transmission of alarm and control signals from the camera site.
- ▲ Video bandwidth of 10MHz
- ▲ Full duplex 2-wire audio intercom with 100Hz to 5kHz bandwidth and associated on hook/off hook signalling with industry standard RJ11 connector
- ▲ Operating range of at least 3km on multimode and 100km on singlemode fiber, depending on optical devices.
- ▲ Video inputs have 3dB overload capability and can be equalised for up to 300m of coaxial cable.

TYPICAL APPLICATION DESIGN



ORDERING INFORMATION

OSD830AT	Video transmitter with 2 duplex audio and 4 duplex data channels	OSD830BR	Video receiver with audio and data to camera
OSD830AR	Video receiver with 2 duplex audio and 4 duplex data channels	Option C	Module version
OSD830BT	Video transmitter with audio and data to camera	Option L	1310nm operation singlemode or multimode
		Option LDN	300nm and 1550nm lasers: Contact factory
		Option W	Single fiber operation



SPECIFICATIONS

ELECTRICAL

Video Input/Output Impedance	75Ω
Video Input/Output Level	1V _{pp} nominal
Video Connector	BNC
Video Bandwidth	5Hz to 10MHz ±1dB
Video Distortion	<0.5% DG, <0.5° DP
Weighted Video Signal to Noise Ratio	>67dB at all receive levels over the unit's full dynamic range
Audio Input/Output Impedance	>10KΩ/<200Ω
Audio Bandwidth	10Hz - 22kHz ±1dB
Audio Input & Output Level	0dBu (0.775V _{rms}) nominal, balanced or unbalanced
Audio Headroom	20dB balanced, 15dB unbalanced
Audio Signal to Noise Ratio	>100dB at maximum level
Audio Distortion	<0.02%
Data Interface	TTL, RS232, RS422 and RS485
Data Rate	31kHz Manchester or Biphasic possible in either direction DC to >400kbps on 3 data channels DC to >100bps on relay channel
Audio and Data Connectors	26 pin female subminiature high density D connector RJ11 for 2-wire intercom

OPTICAL

Transmitter Wavelength	850nm (1310nm for OSD830TL or OSD830RL options)
OSD830T Transmitter Coupled Power	-15 to -5dBm into multimode fiber -15 to -3dBm into singlemode fiber (OSD830TL version only)
OSD830R Transmitter Coupled Power	-20 to -14dBm into multimode fiber -20 to -10dBm into singlemode fiber (OSD830RL version only)
OSD830R Receiver Sensitivity	<-29dBm
OSD830R Receiver Saturation	>-3dBm
OSD830T Sensitivity	<-37dBm
OSD830T Receiver Saturation	>-10dBm
Link Distances	>2km multimode for standard 850nm OSD830 link (fiber bandwidth limited) >3km multimode for optional 1310nm OSD830L link (fiber bandwidth limited) >30km singlemode for optional 1310nm OSD830L link (fiber loss limited)
Optical Connectors	ST standard, others optional

PHYSICAL

	OSD830T	OSD830R
Dimensions of Module (mm)	104W x 144D x 25H	
Weight of Module	400g	
Dimensions of Card (mm)	25W x 208D x 100H	
Weight of Card	200g	
Power Requirement	+10V to 24VDC @ 5VA	
Operating Temperature	-20 to +75°C	
Relative Humidity	0 to 95% non-condensing	
Indicators	Laser OK Tx Video Present Rx Data Present Optical Signal OK	Laser OK Rx Video Present Rx Data Present Optical Signal OK

Chassis Current Consumption (CCC)	0.40 Amp	0.40 Amp
-----------------------------------	----------	----------

DB26 PIN CONFIGURATION

FUNCTION	PIN	FUNCTION	PIN	FUNCTION	PIN	FUNCTION	PIN
Data ground	1,6	Data2 input+	20	Relay input	22	Audio1 output+	16
Audio ground	15,18	Data2 input-	3	Relay output n.o	5	Audio1 output-	25
Data1 input+	10	Data2 output+	12	Relay output n.c	14	Audio2 input+	8
Data1 input-	19	Data2 output-	21	Relay output common	23	Audio2 input-	17
Data1 output+	2	RS232 input	4	Audio1 input+	24	Audio2 output+	26
Data1 output-	11	RS232 output	13	Audio1 input-	7	Audio2 output-	9

Doc ID: 10283006